

Internet Connection Procedure for PANTECH FWP.

(For Windows XP)

- 1. Insert the 'CD' provided by MTNL into CD Drive. The CD content should contain folder named USB_HTP801_HTT801_V1.0**
- 2. Connect one end of the Data Cable to phone and other end to the USB port of PC/Laptop.**
- 3. "Found New Hardware Wizard" will appear on the screen.**
(OPTIONAL STEP)
(If this does not come on PC screen, go to
 - a) Right click on my computer, select PROPERTIES, then HARDWARE, then DEVICE MANAGER**
 - b) In device manager find out the line QUALCOMM CDMA TECHNOLOGY with yellow exclamation symbol**
 - c) Right click on QUALCOMM CDMA TECHNOLOGY and select properties.**
 - d) select reinstall driver)**
- 4. Select "Yes, this time only" and click "Next"**
- 5. Select "Install the software automatically (Recommended)" and click "Next"**
- 6. The process of installing "HANTEL USB Modem" will start.**
- 7. Select "Continue Anyway" and click "Next".**
- 8. The HANTEL USB Modem will be installed successfully.**
- 9. Click on "Finish"**
- 10. Go to "Network Connection" option from "Control Panel".**
- 11. Select "Create New Connection".**
- 12. "Network Connection Wizard" will appear on the screen.**
- 13. Select "Connect to the Internet" option and Click "next"**
- 14. Select "Set up my connection manually", Click Next.**
- 15. Select "Connect using Dial up Modem", Next.**
- 16. (OPTIONAL STEP) Select "HANTEL USB Modem" only from the list of modems., click "Next"**
- 17. Write "mtnl" as ISP name. (You can write any name)**
- 18. Enter "#777" as Phone Number.**
- 19. Type :**
User Name : mtnl
Password : mtnl1234
Confirm Password : mtnl1234.
- 21. Select "Add a shortcut to this connection to my desktop", Click on "Finish" and complete the network connection Wizard.**
- 22. Now Connect to the Internet by selecting DIAL in just prepared Dialup connection**
and surf using any browser.

***** This procedure is for Windows XP. Procedure will slightly vary as per software.**